



Arma™

CO Alarm Troubleshooting Guide

Model

NV968

Battery Type

Sealed 3V lithium, non replaceable

Temperature Range

-10°C to +40°C

Humidity Range

30%RH to 90%RH

[Click here for User Guide](#)

or browse to <https://newfield.help/nv968>

PROBLEM	CAUSE	SOLUTION
The alarm sounds a short beep and the Red LED flashes simultaneously every minute.	The battery is low.	The alarm will need to be replaced.
The alarm beeps 3 times and the Yellow LED flashes simultaneously every 48 seconds.	The alarm has reached the end of its life.	The alarm will need to be replaced.
The alarm beeps twice and the Yellow LED flashes simultaneously every minute.	The alarm is defective.	The alarm will need to be replaced.
The alarm beeps 4 times quickly and the Red LED flashes simultaneously every 5 seconds but you can find nothing which could be emitting carbon monoxide.	The alarm has had a false activation.	Depress the Test/Silence button to silence the alarm and as a precaution ventilate the area. The alarm can be activated by things such as methane, propane, alcohol-based-products, paints, thinners, solvents, adhesives, hairsprays, after shaves, perfumes and cleaning supplies.